

531,009

## (12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property  
Organization  
International Bureau



12 APR 2005




(43) International Publication Date  
27 May 2004 (27.05.2004)

PCT

(10) International Publication Number  
**WO 2004/045061 A1**

- (51) International Patent Classification<sup>7</sup>: **H02P 6/08**, 6/16 (74) Agent: **KEITH W NASH & CO**; 90-92 Regent Street, Cambridge CB2 1DP (GB).
- (21) International Application Number:  
PCT/GB2003/004762 (81) Designated States (*national*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BW, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.
- (22) International Filing Date:  
6 November 2003 (06.11.2003) (84) Designated States (*regional*): ARIPO patent (BW, GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, RO, SE, SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).
- (25) Filing Language: English
- (26) Publication Language: English
- (30) Priority Data:  
0226317.6 9 November 2002 (09.11.2002) GB
- (71) Applicant (*for all designated States except US*): **CAMBRIDGE CONSULTANTS LIMITED** [GB/GB]; Science Park, Milton Road, Cambridge CB4 0DW (GB).
- (72) Inventors; and
- (75) Inventors/Applicants (*for US only*): **GORDON, Benjamin, Morris** [GB/GB]; 95 Fishers Lane, Cherry Hinton, Cambridge CB1 9HL (GB). **BOWYER, Robert, Owen** [GB/GB]; 56 Bartlow Road, Linton, Cambridgeshire CB1 6LY (GB).
- Published:  
— with international search report
- For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.*

(54) Title: CONTROLLER FOR A SYNCHRONOUS MOTOR



(57) Abstract: A controller for a synchronous motor, the controller being operable in use to receive from sensor means coupled to a synchronous motor actual angular displacement signals representative of angular displacements from a reference orientation of a rotor of a synchronous motor, to transmit the actual angular displacement signals to a controllable alternating current (ac) supply for the motor, periodically to measure one or more parameters related to the torque of a synchronous motor, and between transmissions of the actual angular displacement signals, to derive from the actual angular displacement signals and measured parameters at least one estimated angular displacement signal representative of an estimated angular displacement from a reference orientation of a rotor of a synchronous motor, to enable the controller to cause to flow between the supply and a synchronous motor a generally sinusoidal current that is synchronised to the angular displacement of the rotor from the reference orientation.

WO 2004/045061 A1

## CONTROLLER FOR A SYNCHRONOUS MOTOR

### **Field of the Invention**

This invention relates to a controller for a synchronous motor, to a synchronous motor drive that includes such a controller, and to a method of controlling a synchronous motor.

### **Background to the Invention**

Synchronous motor drives, in which angular displacement from a reference orientation of the rotor of a synchronous motor is measured, and each winding of the motor is supplied with an alternating current that is generally synchronised to the angular displacement of the rotor, are well known.

The waveform of the alternating current that can be supplied to each winding of the motor is determined by the resolution of the sensor used to measure the angular displacement of the rotor. For a three-phase motor, for example, the sensor must be capable of measuring the angular displacement of the rotor at least six times during each revolution. If such a sensor is used, the waveform of the current supplied to each winding will be trapezoidal. If instead a high-accuracy resolver is used, capable of measuring the angular displacement of the rotor at least several hundred times during each rotation, the waveform of the current supplied to each winding may be a much closer approximation to sinusoidal.

If the motor is to be supplied with trapezoidal currents, the sensor required is inexpensive, but the trapezoidal currents will cause the motor to produce torque pulsations, leading to relatively noisy operation of the motor.

If the motor is to be supplied with sinusoidal currents, the operation of the motor will be relatively quiet, but the sensor required is expensive, and may even be the most expensive component of the synchronous motor drive.

In an attempt to enable a synchronous motor to be supplied with sinusoidal currents, whilst avoiding the need for a high-resolution sensor, a controller has been developed that receives angular displacement measurements from a low-resolution sensor, and employs a phase-locked loop to generate a pulse train of a frequency determined by the interval between the most recent two angular displacement measurements. The pulse train from the phase-locked loop replaces the angular displacement measurements that would otherwise have been supplied by a high-resolution sensor, and allows the motor to be supplied with substantially sinusoidal currents. Whilst this arrangement results in good synchronisation of the sinusoidal currents to the angular displacement of the rotor under steady-state rotor angular velocity conditions, under transient rotor angular velocity conditions the synchronisation is poor, resulting in noisy operation, and even stalling, of the motor.

A controller has also been proposed that would implement a mathematical model of the motor of sufficient accuracy, would measure the voltage applied to, and current flowing in, each winding of the motor sufficiently frequently, and process the measurements sufficiently quickly, to enable the controller to predict the angular displacement of the rotor, such that no sensor would be required at all. It is likely that the proposed controller would be even more expensive than the high-accuracy resolvers used at present.

### **Summary of the Invention**

According to a first aspect of the invention there is provided a controller for a synchronous motor, the controller being operable in use to receive from sensor means coupled to a synchronous motor actual angular displacement signals representative of angular displacements from a reference orientation of a rotor of a synchronous motor, to transmit the actual angular displacement signals to a controllable alternating current (ac) supply for the motor, periodically to measure one or more parameters related to the torque of a synchronous motor, and between transmissions of the actual angular displacement signals, to derive from the actual angular displacement signals and measured parameters at least one estimated angular displacement signal representative of an estimated angular displacement from a reference orientation of a rotor of a synchronous motor, to enable the

controller to cause to flow between the supply and a synchronous motor a generally sinusoidal current that is synchronised to the angular displacement of the rotor from the reference orientation.

The invention therefore provides a controller for use with a synchronous motor that enables each winding of a motor to be supplied with a generally sinusoidal current, and which requires only a relatively low-resolution shaft position sensor, but which provides improved synchronisation of the sinusoidal current to the angular displacement of the rotor under transient rotor angular velocity conditions.

The one or more parameters related to a torque of a synchronous motor may advantageously include a voltage across, or a current flowing in, a winding of the motor. Alternatively or in addition, the one or more parameters may advantageously include a characteristic of a load coupled to the motor, for example, a pressure developed by a pump driven by the motor.

In a preferred embodiment the controller is operable to store a mathematical model of a synchronous motor, and to derive the at least one estimated angular displacement signal by inserting the measured parameters into the mathematical model.

In the preferred embodiment the controller is operable periodically to receive a first signal proportional to a voltage applied across a winding of a synchronous motor, and a second signal proportional to a current flowing between the supply and the motor, said first and second signals constituting said parameters.

Preferably the controller is operable, upon receiving an actual angular displacement signal, to subtract an estimated angular displacement signal from the actual angular displacement signal, to generate an angular displacement error signal and to adjust the mathematical model so as to reduce the magnitudes of subsequent angular displacement error signals.

In the preferred embodiment the controller is operable periodically to derive from the actual angular displacement signals and measured parameters an estimated angular velocity signal representative of an estimated angular velocity of the rotor, and to transmit the estimated angular velocity signal to an angular velocity governor.

According to a second aspect of the invention there is provided a synchronous motor drive comprising a controller in accordance with the first aspect of the invention, a synchronous motor, a controllable alternating current (ac) supply, and sensor means coupled to a rotor of the motor and operable periodically to transmit to the controller an actual angular displacement signal representative of an angular displacement from a reference orientation of the rotor, the controllable ac supply being operable to receive actual and estimated angular displacement signals from the controller and, in response to the angular displacement signals, to supply to each winding of the motor a generally sinusoidal current that is synchronised to the angular displacement of the rotor from the reference orientation.

Preferably the controllable ac supply is a PWM inverter.

Preferably the PWM inverter is a three-phase inverter and the synchronous motor is a three-phase synchronous motor.

Preferably the synchronous motor is a permanent-magnet synchronous motor.

The sensor means may advantageously comprise a plurality of Hall effect sensors.

Preferably the sensor means comprises three Hall effect sensors, which are so arranged relative to the motor as to generate an actual angular displacement signal for each 60° of angular displacement of the rotor from the reference orientation.

Preferably the controller is operable to measure the one or more parameters related to the speed of the motor and to transmit an actual or estimated angular displacement signal to the controllable ac supply at intervals that are much less than a response time of the motor.

It is to be appreciated that the response time of the motor varies with, amongst other factors, inertia of a load coupled to the rotor, and temperature of the motor windings. Nevertheless, the synchronous motor drive will operate satisfactorily if the controller is operable to transmit at least several hundred angular displacement signals to the controllable ac supply during each revolution of the rotor.

Where the controller is operable to transmit estimated angular velocity signals to a governor, the synchronous motor drive may advantageously further comprise a governor operable to receive estimated angular velocity signals from the controller, to subtract the estimated angular velocity signals from a demanded angular velocity signal representative of a demanded angular velocity of the rotor set by a user of the drive, so as to generate an angular velocity error signal, and to cause the controllable ac supply to increase or decrease the amplitude of the generally sinusoidal current so as to reduce the magnitudes of the angular velocity error signals.

According to a third aspect of the invention there is provided a method of controlling a synchronous motor, comprising the steps of receiving from sensor means coupled to a synchronous motor an actual angular displacement signal representative of an angular displacement from a reference orientation of a rotor of the motor, transmitting the actual angular displacement signal to a controllable alternating current (ac) supply, measuring one or more parameters related to an angular acceleration of the rotor, deriving, using a mathematical model of the motor, from the actual displacement signal and the one or more parameters an estimated angular displacement signal representative of an estimated angular displacement of the rotor, transmitting the estimated angular displacement signal to the controllable ac supply, and thereby causing to flow between the controllable ac supply and the motor a generally sinusoidal current that is synchronised to the angular displacement of the rotor.

Preferably the method further comprises the step of measuring the one or more parameters related to an angular acceleration of the rotor, deriving, using the mathematical model,

from the estimated angular displacement and the one or more parameters a further estimated angular displacement signal representative of an estimated angular displacement of the rotor, and transmitting the further estimated angular displacement signal to the controllable ac supply.

Preferably the method further comprises the step, upon receipt of an actual angular displacement signal, of comparing the actual angular displacement signal with a further estimated angular displacement signal to generate an angular displacement error signal, and adjusting the mathematical model so as to reduce the magnitude of subsequent angular displacement signals.

### **Brief Description of the Drawings**

The invention will now be described by way of illustrative example and with reference to the accompanying drawings, in which:

Figure 1 is a block diagram of a synchronous motor drive in accordance with the second aspect of the invention; and

Figure 2 is a block diagram of a motor modeller forming part of a controller in accordance with the first aspect of the invention.

### **Detailed Description of an Embodiment**

The synchronous motor drive 10 of Figure 1 comprises a three-phase permanent-magnet synchronous motor 12, a rotor angular displacement sensor 14, a three-phase bridge 16 controlled by a sinusoidal pulse-width modulated (PWM) signal generator 18, a rotor angular velocity governor indicated generally by reference numeral 20 and a discrete-time controller indicated generally by reference numeral 22.

The rotor angular displacement sensor 14 is attached to a shaft of the motor 12 and is made up of three Hall effect sensors (not shown), so arranged that an actual angular displacement signal, representative of an angular displacement of a rotor of the motor from

a reference orientation, is generated for each 60° of angular displacement of the rotor from the reference orientation. The frequency at which actual angular displacement signals are generated by the rotor angular displacement sensor is therefore determined by the angular velocity of the rotor.

The three-phase bridge 16 is connected between a direct current power supply (not shown) and the motor 12 and causes generally sinusoidal currents to flow between the supply and each winding of the motor.

The PWM signal generator 18 is connected to the bridge 16, the governor 20 and the controller 22. It receives angular displacement signals from the controller and demanded voltage signals from the governor, and transmits to the bridge 16 sinusoidal PWM signals of fundamental frequencies determined by the angular displacement signals and duty ratios determined by the demanded voltage signals.

The governor 20 receives demanded angular velocity signals from a user of the drive and predicted angular velocity signals from the controller 22, and transmits to the PWM signal generator 18 demanded voltage signals so as to make the predicted angular velocity signals equal to the demanded angular velocity signals.

The controller 22 samples the outputs of the rotor angular displacement sensor 14, bridge 16 and governor 20 with a sampling frequency of 1 kHz and generates and transmits control signals to the PWM signal generator 18 and governor 20 at the sampling frequency. The sampling frequency of 1 kHz is selected such that the PWM signal generator 18 receives at least one hundred angular displacement signals during each revolution of the rotor for angular velocities of the rotor up to 600 revolutions per minute.

The output of the rotor angular displacement sensor 14 is sampled by the controller 22 to generate actual angular displacement samples,  $\theta_{\text{actual}}$ . The actual angular displacement signals generated by the sensor are of relatively short duration and will in general each occupy only one actual angular displacement sample. If the rotor is rotating at 600



revolutions per minute, say, the rotor angular displacement sensor will generate actual angular displacement signals at 60 Hz. Since the output of the rotor angular displacement sensor is sampled at 1 kHz, only a minority of the actual angular displacement samples will be samples of actual angular displacement signals, and the remainder of the actual angular displacement samples will be zero.

The controller also samples the currents flowing between the supply and each winding of the motor to generate actual motor current samples,  $i_{\text{actual}}$ , and samples the demanded voltage signal transmitted to the PWM signal generator 18 by the governor 20 to generate demanded voltage samples,  $v_{\text{demanded}}$ . Every millisecond the controller generates a predicted angular displacement signal,  $\theta_{\text{predicted}}$ , and transmits to the PWM signal generator 18 either an actual angular displacement sample, if the most recent angular displacement sample is non-zero, or the predicted angular displacement signal, if the angular displacement sample is zero. At the same time, the controller also generates a predicted angular velocity signal,  $\omega_{\text{predicted}}$ , and transmits the predicted angular velocity signal to the governor 20.

The governor 20 is made up of an angular velocity signal comparator 24 and a demanded voltage signal generator 26. The angular velocity signal comparator receives demanded angular velocity signals,  $\omega_{\text{demanded}}$ , representative of angular velocities of the rotor demanded by a user of the drive, and predicted angular velocity signals from the controller 22, subtracts the predicted angular velocity signals from the demanded angular velocity signals to generate angular velocity error signals,  $v_{\text{error}}$ , and transmits the angular velocity error signals to the demanded voltage signal generator 26. The demanded voltage signal generator generates demanded voltage signals so as to reduce the magnitude of the angular velocity error signals.

The controller 22 is made up of a motor modeller 28, an angular displacement predictor 30, a resistance trimmer 32, a proportional-integral (PI) controller 34 and current signal and angular displacement signal comparators 36 and 38 respectively.

Each millisecond an actual angular displacement sample is received by the angular displacement predictor 30 and angular displacement signal comparator 38. At the same time the angular displacement signal comparator receives a predicted angular displacement signal from the angular displacement predictor. If the actual angular displacement sample is zero, it is disregarded by both the angular displacement predictor and the angular displacement signal comparator. If, on the other hand, the actual angular displacement sample corresponds to an actual angular displacement signal, it is transmitted by the angular displacement predictor to the PWM signal generator, and subtracted by the angular displacement signal comparator from the most recently received predicted angular displacement signal to generate an angular displacement error signal,  $\theta_{\text{error}}$ , which is transmitted by the angular displacement signal comparator to the resistance trimmer 32. The resistance trimmer 32 therefore receives angular displacement error signals at approximately the same frequency as the rotor angular displacement sensor generates actual angular displacement signals.

In response to each angular displacement error signal the resistance trimmer 32 generates a resistance trim signal,  $\Delta_{\text{resistance}}$ , representative of an adjustment to a nominal value of the resistance of the windings of the motor, so as to reduce the magnitude of subsequent angular displacement error signals. The resistance trimmer 32 is designed primarily to enable the motor modeller 28 to compensate for inaccuracies of the model due to changes in the resistance of the windings of the motor with temperature. However, to a limited extent, the resistance trimmer is also able to compensate for other inaccuracies of the model, for example changes in the inertia of the rotor with angular velocity.

Each millisecond an actual motor current sample is received by the current signal comparator 36, together with a predicted motor current signal,  $i_{\text{predicted}}$ , generated by the motor modeller 28. The current signal comparator subtracts the predicted motor current signal from the actual motor current sample to generate a motor current error signal,  $i_{\text{error}}$ , which it transmits to the PI controller 34.

The PI controller generates estimated load torque signals,  $T_{\text{estimated}}$ , and transmits the estimated load torque signals to the motor modeller 28. The motor modeller generates the predicted motor current signals from the estimated torque signals, which are generated by the PI controller so as to reduce the magnitudes of subsequent motor current error signals.

The motor modeller 28 samples the demanded voltage signals generated by the demanded voltage signal generator 26 every millisecond and generates from the demanded voltage sample and estimated load torque signal a predicted rotor angular velocity signal,  $\omega_{\text{predicted}}$ , which it transmits to the rotor angular displacement predictor 30 and angular velocity signal comparator 24.

The angular displacement predictor 30 stores the most recent actual angular displacement signal from the rotor angular displacement sensor, and generates a predicted angular displacement signal by integrating the predicted rotor angular velocity signal and adding the integrated signal to the stored actual angular displacement signal. Subsequent estimated angular displacement signals are generated by integrating subsequent predicted angular velocity signals from the motor modeller and adding the integrated signal to the previous estimated angular displacement signal.

Turning next to Figure 2, which shows the motor modeller 28 in greater detail, the motor modeller is made up of a signal processor 40, a resistance memory 42 containing a nominal value for the resistance of the motor windings, an inductance memory 44 containing a nominal value for the inductance of the motor windings, an inertia memory 46 containing a nominal value for the inertia of the rotor and any load attached thereto, an angular velocity signal amplifier 48, a current signal amplifier 50, a voltage signal comparator 52, a resistance signal adder 54, a load torque signal comparator 56, an attenuator 58 and an integrator 60.

The voltage signal comparator 52 receives a demanded voltage sample,  $V_{\text{demanded}}$ , and a predicted back emf signal,  $e_{\text{back}}$ , from the angular velocity signal amplifier 48, subtracts the predicted back emf signal from the demanded voltage sample to generate a predicted

winding voltage,  $v_{\text{predicted}}$ , representative of a predicted voltage developed across each winding of the motor, and transmits the predicted winding voltage to the signal processor 40.

Whenever the resistance signal adder 54 receives a resistance trim signal,  $\Delta_{\text{resistance}}$ , from the resistance trimmer (not shown in Figure 2), it adds the resistance trim signal to the nominal value,  $R_{\text{nominal}}$ , of the motor winding resistance stored in the resistance memory 42 and transmits the resulting trimmed resistance value,  $r_{\text{trimmed}}$ , to the signal processor 40, which stores the trimmed resistance value. The inductance memory 44 transmits the nominal motor winding inductance value,  $L_{\text{nominal}}$ , to the signal processor 40, which stores the inductance value.

The signal processor generates a predicted motor current,  $i_{\text{predicted}}$ , from the predicted winding voltage,  $v_{\text{predicted}}$ , trimmed resistance value,  $r_{\text{trimmed}}$ , nominal inductance value,  $L_{\text{nominal}}$ , and previous predicted motor currents, from which a rate of change of motor current is derived. The predicted motor current is transmitted to the current signal comparator (not shown in Figure 2), and to the current signal amplifier 50.

The current signal amplifier has a gain corresponding to the torque constant of the motor, and converts the predicted motor current signal into an estimated total torque signal,  $T_{\text{total}}$ , representative of the total torque produced by the motor as a result of the predicted motor current. The torque signal comparator receives the estimated total torque signal and an estimated torque signal,  $T_{\text{estimated}}$ , from the PI controller (not shown in Figure 2), subtracts the estimated load torque from the total torque signal to generate a resultant torque signal,  $T_{\text{resultant}}$ , which it transmits to the attenuator 58.

The attenuator has an attenuation determined by a nominal inertia value,  $J_{\text{nominal}}$ , stored in the inertia memory 46, and divides the resultant torque signal by the nominal inertia value to generate a predicted rotor angular acceleration signal,  $d\omega_{\text{predicted}}/dt$ , which it transmits to the integrator 60. The integrator 60 integrates the predicted rotor angular acceleration signal to generate a predicted rotor angular velocity signal,  $\omega_{\text{predicted}}$ , which it transmits to

the rotor angular displacement predictor (not shown in Figure 2) and to the angular velocity signal amplifier 48.

The angular velocity signal amplifier has a gain corresponding to the emf constant of the motor and converts the predicted angular velocity signal into a predicted back emf signal representative of the predicted back emf,  $e_{back}$ , of the motor, and transmits the predicted back emf signal to the voltage signal comparator 52.

It will be apparent that the above description relates only to one embodiment of the invention, and that the invention encompasses other embodiments as defined by the statements of the invention.

### Claims

1. A controller for a synchronous motor, the controller being operable in use to receive from sensor means coupled to a synchronous motor actual angular displacement signals representative of angular displacements from a reference orientation of a rotor of a synchronous motor, to transmit the actual angular displacement signals to a controllable alternating current (ac) supply for the motor, periodically to measure one or more parameters related to the torque of a synchronous motor, and between transmissions of the actual angular displacement signals, to derive from the actual angular displacement signals and measured parameters at least one estimated angular displacement signal representative of an estimated angular displacement from a reference orientation of a rotor of a synchronous motor, to enable the controller to cause to flow between the supply and a synchronous motor a generally sinusoidal current that is synchronised to the angular displacement of the rotor from the reference orientation.
2. A controller according to claim 1, which is operable periodically to measure one or more parameters related to a torque of a synchronous motor, which parameters include a voltage across, or a current flowing in, a winding of the motor.
3. A controller according to claim 1 or claim 2, which is operable periodically to measure one or more parameters related to a torque of a synchronous motor, which parameters include a characteristic of a load coupled to the motor.
4. A controller according to any preceding claim, which is operable to store a mathematical model of a synchronous motor, and to derive the at least one estimated angular displacement signal by inserting the measured parameters into the mathematical model.
5. A controller according to any preceding claim, which is operable periodically to receive a first signal proportional to a voltage applied across a winding of a synchronous

motor, and a second signal proportional to a current flowing between the supply and the motor, said first and second signals constituting said parameters.

6. A controller according to any preceding claim, which is operable, upon receiving an actual angular displacement signal, to subtract an estimated angular displacement signal from the actual angular displacement signal, to generate an angular displacement error signal and to adjust the mathematical model so as to reduce the magnitudes of subsequent angular displacement error signals.

7. A controller according to any preceding claim, which is operable periodically to derive from the actual angular displacement signals and measured parameters an estimated angular velocity signal representative of an estimated angular velocity of the rotor, and to transmit the estimated angular velocity signal to an angular velocity governor.

8. A synchronous motor drive comprising a controller in accordance with any of claims 1 to 7, a synchronous motor, a controllable alternating current (ac) supply, and sensor means coupled to a rotor of the motor and operable periodically to transmit to the controller an actual angular displacement signal representative of an angular displacement from a reference orientation of the rotor, the controllable ac supply being operable to receive actual and estimated angular displacement signals from the controller and, in response to the angular displacement signals, to supply to each winding of the motor a generally sinusoidal current that is synchronised to the angular displacement of the rotor from the reference orientation.

9. A synchronous motor drive according to claim 8, wherein the controllable ac supply is a PWM inverter.

10. A synchronous motor drive according to claim 9, wherein the PWM inverter is a three-phase inverter and the synchronous motor is a three-phase synchronous motor.

11. A synchronous motor drive according to any of claims 8 to 10, wherein the synchronous motor is a permanent-magnet synchronous motor.
12. A synchronous motor drive according to any of claims 8 to 11, wherein the sensor means comprises a plurality of Hall effect sensors.
13. A synchronous motor drive according to claim 12, wherein the sensor means comprises three Hall effect sensors, which are so arranged relative to the motor as to generate an actual angular displacement signal for each 60° of angular displacement of the rotor from the reference orientation.
14. A synchronous motor drive according to any of claims 8 to 13, wherein the controller is operable to measure the one or more parameters related to the speed of the motor and to transmit an actual or estimated angular displacement signal to the controllable ac supply at intervals that are much less than a response time of the motor.
15. A synchronous motor drive according to any of claims 8 to 14 when dependent from claim 7, which further comprises a governor operable to receive estimated angular velocity signals from the controller, to subtract the estimated angular velocity signals from a demanded angular velocity signal representative of a demanded angular velocity of the rotor set by a user of the drive, so as to generate an angular velocity error signal, and to cause the controllable ac supply to increase or decrease the amplitude of the generally sinusoidal current so as to reduce the magnitudes of the angular velocity error signals.
16. A method of controlling a synchronous motor, comprising the steps of receiving from sensor means coupled to a synchronous motor an actual angular displacement signal representative of an angular displacement from a reference orientation of a rotor of the motor, transmitting the actual angular displacement signal to a controllable alternating current (ac) supply, measuring one or more parameters related to an angular acceleration of the rotor, deriving, using a mathematical model of the motor, from the actual displacement signal and the one or more parameters an estimated angular displacement



signal representative of an estimated angular displacement of the rotor, transmitting the estimated angular displacement signal to the controllable ac supply, and thereby causing to flow between the controllable ac supply and the motor a generally sinusoidal current that is synchronised to the angular displacement of the rotor.

17. A method according to claim 16, which further comprises the step of measuring the one or more parameters related to an angular acceleration of the rotor, deriving, using the mathematical model, from the estimated angular displacement and the one or more parameters a further estimated angular displacement signal representative of an estimated angular displacement of the rotor, and transmitting the further estimated angular displacement signal to the controllable ac supply.

18. A method according to claim 17, which further comprises the step, upon receipt of an actual angular displacement signal, of comparing the actual angular displacement signal with a further estimated angular displacement signal to generate an angular displacement error signal, and adjusting the mathematical model so as to reduce the magnitude of subsequent angular displacement signals.




Fig. 1




Fig. 2

# INTERNATIONAL SEARCH REPORT

International Application No  
PCT/GB 03/04762

A. CLASSIFICATION OF SUBJECT MATTER  
IPC 7 H02P6/08 H02P6/16

According to International Patent Classification (IPC) or to both national classification and IPC

## B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)  
IPC 7 H02P

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the International search (name of data base and, where practical, search terms used)

EPO-Internal, WPI Data

## C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US 4 390 826 A (ERDMAN DAVID M ET AL) 28 June 1983 (1983-06-28) column 2, line 26 - column 6, line 23; figures 1,4	1-18
A	US 6 091 216 A (TAKAHASHI HISASHI ET AL) 18 July 2000 (2000-07-18) column 2, line 15 - column 4, line 4; figures 2,4,5	1-18
A	US 5 287 044 A (IZAWA HIROKAZU ET AL) 15 February 1994 (1994-02-15) abstract; figures 1,2	1-18
A	US 5 486 743 A (NAGAI KAZUNOBU) 23 January 1996 (1996-01-23)	
	-/--	

☒ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

### \* Special categories of cited documents:

- \*A\* document defining the general state of the art which is not considered to be of particular relevance
- \*E\* earlier document but published on or after the international filing date
- \*L\* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- \*O\* document referring to an oral disclosure, use, exhibition or other means
- \*P\* document published prior to the international filing date but later than the priority date claimed

- \*T\* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- \*X\* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- \*Y\* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- \*Z\* document member of the same patent family

Date of the actual completion of the International search

5 March 2004

Date of mailing of the International search report

12/03/2004

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2  
NL - 2280 HV Rijswijk  
Tel (+31-70) 340-2040, Tx. 31 651 epo nl,  
Fax (+31-70) 340-3016

Authorized officer

Segaert, P

# INTERNATIONAL SEARCH REPORT

International Application No

PCT/GB 03/04762

## C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	EP 1 087 516 A (MTS SYSTEM CORP) 28 March 2001 (2001-03-28)	
A	EP 1 111 766 A (HITACHI LTD) 27 June 2001 (2001-06-27)	

# INTERNATIONAL SEARCH REPORT

International Application No  
PCT/GB 03/04762

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 4390826	A	28-06-1983	US 4005347 A	25-01-1977
			CA 1140658 A1	01-02-1983
			DE 3175366 D1	30-10-1986
			DE 3177002 D1	13-04-1989
			DE 3177268 D1	30-01-1992
			EP 0038694 A1	28-10-1981
			EP 0146673 A1	03-07-1985
			EP 0218017 A1	15-04-1987
			US 4532459 A	30-07-1985
			US 5376866 A	27-12-1994
			US 4513230 A	23-04-1985
			US 4556827 A	03-12-1985
			US 4449079 A	15-05-1984
			US 5023527 A	11-06-1991
			US 5125067 A	23-06-1992
			US 5227704 A	13-07-1993
			AR 213272 A1	15-01-1979
			BR 7503972 A	06-07-1976
			CA 1035008 A1	18-07-1978
			DE 2527744 A1	15-01-1976
			DK 286575 A ,B,	25-12-1975
			FR 2276723 A1	23-01-1976
			IT 1044299 B	20-03-1980
			US RE35124 E	19-12-1995
			US 4459519 A	10-07-1984
			US 4654566 A	31-03-1987
			US 5075608 A	24-12-1991
			US 4169990 A	02-10-1979
US 6091216	A	18-07-2000	EP 0961396 A1	01-12-1999
US 5287044	A	15-02-1994	JP 5122978 A	18-05-1993
US 5486743	A	23-01-1996	JP 6165569 A	10-06-1994
			JP 3337769 B2	21-10-2002
			JP 7067380 A	10-03-1995
			GB 2272808 A ,B	25-05-1994
			GB 2305314 A ,B	02-04-1997
			KR 140362 B1	17-08-1998
EP 1087516	A	28-03-2001	US 6307336 B1	23-10-2001
			EP 1087516 A2	28-03-2001
EP 1111766	A	27-06-2001	JP 3341826 B2	05-11-2002
			JP 2000078888 A	14-03-2000
			EP 1111766 A1	27-06-2001
			US 6626002 B1	30-09-2003
			CN 1320297 T	31-10-2001
			WO 0013302 A1	09-03-2000